


technics



Please make sure that main voltage is disconnected before proceeding!

Name

Reference

L x W x H

Diapason 3-circuit track , 2000mm

kr72602x

2000 x 36 x 32

Diapason 3-circuit track, 3000mm

kr72603x

3000 x 36 x 32


Diapason mounting bracket recessed profile

kr726056


80 x 45 x H

1 dimensions


2 installation






the support profile can be sawed to the length of the building site



the height of bracket can be adjusted to the thickness of the ceiling to ensure a flush mount



installation




rubber grommet

toggle nuts

make sure that the toggle nuts are installed right-side-up


drive the screws into the toggle nuts 3 revolutions only



first turn all screws clockwise 90° until track site flush in the support profile, starting from the middle and working outwards


then go back and tighten all the screws firmly

3 connection




rubber grommet is not included

or



in case of end feed



in case of mid feed

Name

Reference

L x W x H

Diapason end feed earth left

kr72651x

68 x 36 x 32

Diapason end feed earth right

kr72652x

68 x 36 x 32

Diapason mid feed

kr72653x

130 x 36 x 8